



## Selection Guide

(Continued)

	Input Voltage Nominal (Range) (Vdc) *	Output Voltage (Vdc)	Output Current (mA)	Efficiency %	Model Number	Case	
<b>SINGLE OUTPUT VOLTAGE</b>	12 (9-18)	3.3	15000	78	MWA60-12S33	R	
		5	12000	81	MWA60-12S5	R	
		12	5000	82	MWA60-12S12	R	
		15	4000	82	MWA60-12S15	R	
	24 (18-36)	3.3	15000	79	MWA60-24S33	R	
		5	12000	83	MWA60-24S5	R	
		12	5000	84	MWA60-24S12	R	
		15	4000	84	MWA60-24S15	R	
	48 (36-72)	3.3	15000	80	MWA60-48S33	R	
		5	12000	84	MWA60-48S5	R	
		12	5000	85	MWA60-48S12	R	
		15	4000	85	MWA60-48S15	R	
<b>DUAL OUTPUTS</b>	12 (9-18)	±5	+10000 / -2000	81	MWA60-12-5	R	
		±12	±2500	82	MWA60-12-12	R	
		±15	±2000	82	MWA60-12-15	R	
		3.3 / 5.0	600 / 600	79	MWA60-12D33/5	R	
	24 (18-36)	±5	+10000 / -2000	83	MWA60-24-5	R	
		±12	±2500	84	MWA60-24-12	R	
		±15	±2000	84	MWA60-24-15	R	
		3.3 / 5.0	600 / 600	80	MWA60-24D33/5	R	
	48 (36-72)	±5	+10000 / -2000	84	MWA60-48-5	R	
		±12	±2500	85	MWA60-48-12	R	
		±15	±2000	85	MWA60-48-15	R	
		3.3 / 5.0	600 / 600	81	MWA60-48D33/5	R	

**\*NOTE**

For 4:1 Input Voltage, use prefix "MWB60" in place of "MWA60" in model number.

For 9-36Vdc Input, use "24" after "-60".

For 20-72Vdc Input, use "48" after "-60".

(See next page for diagram)

**POLYTRON DEVICES, Inc.**

P.O. Box 398, Paterson, New Jersey 07544 U.S.A.  
Tel: (973)345-5885 Fax: (973)345-1264 • Email: sales@polytrondevices.com • www.polytrondevices.com

